

AUGUST 9, 2017

1

UL 498B

Outline of Investigation for Receptacles with Integral Switching Means

Issue Number: 4

August 09, 2017

Summary of Topics

This is the third issue of the Outline of Investigation for Receptacles with Integral Switching Means, UL 498B. This new issue clarifies the following:

Clarified Insulating material requirements

Added the word "CONTROLLED" to required markings in Supplement SA

Added Input Test

Added Overvoltage and Undervoltage test

UL's Outlines of Investigation are copyrighted by UL. Neither a printed nor electronic copy of an Outline of Investigation should be altered in any way. All of UL's Outlines of Investigation and all copyrights, ownerships, and rights regarding those Outlines of Investigation shall remain the sole and exclusive property of UL.

COPYRIGHT © 2017 UL LLC

No Text on This Page

CONTENTS

INTRODUCTION

1 Scope	6
2 Components	7
3 Units of Measurement	7
4 Undated References	8
5 Glossary	8

CONSTRUCTION

6 General	11
7 Configurations	11
8 Accessibility of Live Parts	11
9 Current-Carrying Parts	13
10 Internal Wiring	13
11 Internal Splices and Connections	13
11.1 General	13
11.2 Wire-wrapped connections	14
11.3 Wiring terminals and leads	15
12 Separation of Circuits	15
13 Insulating Material	17
14 Printed-Wiring Boards	17
15 Components	18
15.1 Switching devices	18
15.2 Capacitors	18
15.3 Power-switching semiconductors	19
15.4 Isolation devices	19
16 Transformers	19
16.1 General	19
16.2 Isolation transformers	20
17 Spacings	21
18 Alternate Spacings – Clearances and Creepage Distances	23
19 Bonding of Internal Parts for Grounding	24
20 Class 2 Circuits	24
21 Class 2 Separable Lead Assembly	27

PERFORMANCE

22 General	28
22A Input Test	28
22B Overvoltage and Undervoltage Test	28
23 Temperature Test	29
23.1 General	29
23.2 Operation	30
23.3 Temperature measurements	30
24 DC Offset Voltage Test	31
25 Abnormal Operation Test	32
25.1 Motor	32
25.2 Component failure	32
25.3 Abnormal switching test	33

26	Limited Power Point Determination Test	34
26.1	General	34
26.2	Option No. 1	34
26.3	Option No. 2	36
26.4	Component failure	36
26.5	Overload test	37
27	Isolation Tests	38
27.1	General	38
27.2	Pulse transformer burnout tests	39
27.3	Optical isolator tests	40
27.4	Component failure	41
28	Power-Switching Semiconductors	41
28.1	General	41
28.2	Overload test	42
28.3	Endurance	43
29	Voltage Surge Test	44
30	Power Supplies – Short circuit	46
31	Component Failure Test	47
32	Electronic Component Evaluation	47
33	Dielectric Voltage-Withstand Test	48
33.1	General	48
33.2	Primary circuits	48
33.3	Isolated secondary circuits	49
33.4	Transformers	50

MANUFACTURING AND PRODUCTION LINE TESTS

34	DC Offset Voltage Test	51
----	------------------------	----

RATING

35	Details	51
35.1	Input	51
35.2	Output	51
35.3	Operational ambient temperature	52

MARKINGS

36	General	52
37	Installation Instructions	53

SUPPLEMENT SA - RECEPTACLES WITH INTEGRAL SWITCHING MEANS INTENDED FOR ENERGY MANAGEMENT AND BUILDING AUTOMATION

INTRODUCTION

SA1	Scope	SA1
-----	-------	-----

CONSTRUCTION

SA2 General	SA1
SA3 Electrical Rating	SA1

PERFORMANCE

SA4 General	SA2
SA5 Overload Test	SA2
SA6 Endurance Test	SA4

RATING

SA7 Details	SA7
SA7.1 Input	SA7
SA7.2 Output	SA8

MARKINGS

SA8 Details	SA8
-------------------	-----

INSTALLATION INSTRUCTIONS

SA9 General	SA11
-------------------	------

APPENDIX A

Standards for Components.....	A1
-------------------------------	----

INTRODUCTION

1 Scope

1.1 These requirements cover a receptacle with integral switching means rated 600 V or less, used in ordinary dry locations and intended for connection to a branch circuit in accordance with the National Electrical Code, NFPA 70.

1.2 A receptacle with integral switching means covered by this Outline shall meet the following requirements:

- a) No voltage greater than 600 V above ground will be present in the device,
- b) An isolation transformer, if provided, will generally furnish power at a lower potential than the primary voltage; and
- c) The output of the device will not be located in a circuit operating at greater than 600 V above ground.
- d) The switching device shall be integral to the receptacle.
- e) A receptacle that is marked with the symbol shown in Table SA8.1 Reference No. 2 and does not employ an integral switching means intended for energy management and building automation, are covered by the Standard for Attachment Plugs and Receptacles, UL 498.

1.3 This Outline does not directly apply to, but may supplement the following standards:

- a) Devices produced integrally with flexible cord or cable, covered by the Standard for Cord Sets and Power-Supply Cords, UL 817;
- b) Current taps and adapters covered by the Standard for Current Taps and Adapters, UL 498A;
- c) Devices employing male or female screwshells, covered by the Standard for Lampholders, UL 496;
- d) Single and multipole connectors intended for factory assembly to copper or copper alloy conductors or printed wiring boards for use in data, signal, control and power applications within and between electrical equipment, covered by the Standard for Component Connectors for Data, Signal, Control and Power Applications, UL 1977;
- e) Devices intended for installation and use in hazardous (classified) locations in accordance with the National Electrical Code, NFPA 70, covered by the Standard for Explosion-Proof and Dust-Ignition-Proof Equipment for Use in Hazardous (Classified) Locations, UL 1203;
- f) Devices intended for use with telecommunications networks, covered by the Standard for Information Technology Equipment – Safety – Part 1: General Requirements, UL 60950-1, or the Standard for Communications Circuit Accessories, UL 1863;
- g) Devices incorporating ground-fault circuit interruption circuitry, covered by the Standard for Ground-Fault Circuit Interrupters, UL 943;

- h) Direct plug-in devices incorporating transient voltage surge suppression circuitry, covered by the Standard for Surge Protective Devices, UL 1449;
- i) Direct plug-in devices incorporating electromagnetic interference filter circuitry, covered by the Standard for Electromagnetic Interference Filters, UL 1283;
- j) Cord-connected, relocatable power taps intended only for indoor use as a temporary extension of a grounding alternating-current branch circuit for general use, covered by the Standard for Relocatable Power Taps, UL 1363.
- k) Energy management equipment covered by the Standard for Energy Management Equipment, UL 916.

2 Components

2.1 Except as indicated in 2.2, a component of a product covered by this Outline shall comply with the requirements for that component. See Appendix A for a list of standards covering components generally used in the products covered by this Outline.

2.2 A component is not required to comply with a specific requirement that:

- a) Involves a feature or characteristic not required in the application of the component in the product covered by this Outline; or
- b) Is superseded by a requirement in this Outline.

2.3 A component shall be used in accordance with its rating established for the intended conditions of use.

2.4 Specific components are incomplete in construction features or restricted in performance capabilities. Such components are intended for use only under limited conditions, such as certain temperatures not exceeding specified limits, and shall be used only under those specific conditions.

3 Units of Measurement

3.1 Values stated without parentheses are the requirement. Values in parentheses are explanatory or approximate information.

3.2 Unless indicated otherwise, voltage and current values specified in this Outline are rms, and wattage values are average power.