II.11.4 Various Relays (Continued)

		Graphica	al symbol	
No.	Name	Series 1	Series 2	Description
II.11.4.32	Directional short- circuit relay	I> (IEC)	(a) (b)	Symbol of series 1 denotes an overcurrent relay operated by energy flow away from a busbar.
II.11.4.33	Directional ground- fault relay	<u>I÷&gt;</u> (IEC)	(a) (b)	Symbol of series 1 denotes a ground-fault overcurrent relay operated by energy flow away from a busbar.
II.11.4.34	Short- circuit selection relay	I <sub>d</sub> /U>	(a) (b) SS	
II.11.4.35	Ground- fault selection relay	[I <sub>d</sub> /U <sub>rsd</sub> >]	(a) (b)	
II.11.4.36	Step-out relay	dZ/dt>	S0	Symbol of series 1 denotes a relay which utilizes a method of detecting the variation of impedance viewed from the relay.
II.11.4.37	Frequency relay	f (IEC)	F	1
II.11.4.38	Time limit relay	(IEC)	(a) (b) TL	
II.11.4.39	Auxiliary relay		(a) (b) Ax	
II.11.4.40	Blocking relay		L	

## II.11.4 Various Relays (Continued)

No	Nama	Graphica	al symbol	
No.	Name	Series l	Series 2	Description
II.11.4.41	Synchro- nizing relay		Sy	Synchronization detecting relay is included.
II.11.4.42	Polarity relay		Pt	-
II.11.4.43	Auto- reclose relay	0 → 1 07-18-02	(a) (b)	
II.11.4.44	Flicker relay		Fc	
II.11.4.45	Fault indicator		, FI —	
II.11.4.46	Temperature relay	θ (IEC)	Т	
II.11.4.47	Pressure relay	(IEC)	Pr	<ol> <li>In series 1, p is written in small letter.</li> <li>Following graphical symbol may be used in series 2: vacuum relay</li> </ol>
II.11.4.48	Shock pressure relay	dp/dt>	SP	

II.11.4 Various Relays (Continued)

No.	Name	Graphical	symbol	Description
NO.		Series 1	Series 2	
II.11.4.49	Flow relay	(IEC)	F2	In series 2, the follow- ing graphical symbols may be used according to the kind of fluid: Oil-flow relay  Olfl  Water-flow relay  Wtfl
II.11.4.50	Gas-flow relay	(IEC)	ArFl	
II.11.4.51	Position relay	(IEC)	Ро	Symbol of series 1 denotes a liquid level relay.
II.11.4.52	Velocity relay	V (IEC)	ν	In series l, V is written in a small letter.
II.11.4.53	Buchholtz relay	<b>⇔</b> □ □ 07-18-01	ВН	
II.11.4.54	Carrier relay (carrier relay system)		Cr	
II.11.4.55	Carrier receiving relay		CrRe	•
II.11.4.56	Directional comparison carrier relay		CrD	

## II.11.4 Various Relays (Continued)

N-	N	Graphical symbol		Dearnistan
No.	иаше	Series 1	Series 2	Description
II.11.4.57	Phase comparison carrier relay		СгФ	
II.11.4.58	Transfer- tripping carrier relay		C+TT_	
II.11.4.59	Pilot- wire relay (Pilot- wire relay system)		Pw	
II.11.4.60	Direc- tional- comparison pilot- wire relay		PwD .	
II.11.4.61	Differ- ential pilot- wire relay		PwDf	
II.11.4.62	Transfer- tripping pilot- wire relay		РwТТ	
II.11.4.63	Pilot- wire monitoring relay		: PwMo	
II.11.4.64	Microwave relay (microwave carrier relay system)		М	·
II.11.4.65	Direc- tional- comparison microwave relay		MD	2

Copyright by the Japanese Industrial Standa This is a preview. Click here to purchase the full publication. Mon Aug 22 01:18:28 2011

JIS C\*0301 90 ■ 4933608 0532308 196 ■

128 C 0301-1990

II.11.4 Various Relays (Continued)

No.	Name	Graphica	l symbol	
-	Name	Series 1	Series 2	Description
II.11.4.66	Phase- comparison microwave relay	-	МФ	2
II.11.4.67	Transfer- tripping microwave relay		MTT]	2
II.11.4.68	Transfer- tripping relay		ŢΤ	2
II.11.4.69	Optical trans- mission relay (Optical trans- mission system)		PCM	

## II.11.5 Examples of Relay Function Combination (Series 1)

No.	Name	Graphica	l symbol	
	Name	Series 1	Series 2	Description
II.11.5.1	Under- voltage relay	U < 5080V 130%	· :	An example of: Setting range 50 to 80 V, Resetting ratio 130 %
II.11.5.2	Over- current relay	<i>I</i> > □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □	·	Time-lag type is exemplified.
II.11.5.3		2(I>) 510A		A relay with two current elements and a setting range from 5 to 10 A is exemplified.

II.11.5 Examples of Relay Function Combination (Series 1) (Continued)

No.	Name	Graphical	symbol	
NO•	иаше	Series l	Series 2	- Description
II.11.5.4	Over- current relay (continued)	<i>I</i> > 5x − 707-17-14		A relay with two outputs, one active at current above five times the setting value, the other with inverse time-lag characteristic is exemplified.
II.11.5.5		$ \begin{array}{c} n \approx 0 \\ I > \\ 07-17-13 \end{array} $		Locked-rotor detection relay operating by current sensing is exemplified.
II.11.5.6	Over and under current relay	$I \gtrsim \frac{5A}{3A}$ $07-17-08$		A relay operating above 5 A and below 3 A is exemplified.
II.11.5.7		Q > 1 Mvar 510 s		A relay in which, energy flow is towards busbar, operation is at reactive power 1 Mvar and time-lag is adjustable from 5 to 10 s, is exemplifield.
II.11.5.8	Interturn short- circuit relay	N < 07-17-10	:	A relay detecting interturn short-circuits is exemplified.

## II.12 Measuring Instrument

- (1) Letter T is prefixed to the symbol for totalizing type.
- (2) Letter Pt is prefixed to the symbol for printing type.
- (3) Letter M is prefixed to the symbol for instruments which can indicate the maximum and minimum values.

II.12.1 Indicating Instrument

No.	Name	Graphical symbol	Description
II.12.1.1	Indicating instrument (general)	08-01-01	<ol> <li>See I.2.5.1 (indicating instrument).</li> <li>Letter or graphical symbol which indicates the kind of instrument is entered in O.</li> <li>Identification of a.c. or d.c., if necessary, is done as follows:         D.C. A.C.</li></ol>
II.12.1.2	Voltmeter	08-02-01	
II.12.1.3	Ammeter	(IEC)	·

II.12.1 Indicating Instrument (Continued)

No.	Name	Graphical symbol	Description
II.12.1.4	Ohm meter	(D)	
II.12.1.5	High-low voltmeter	HLV	
II.12.1.6	Watt- meter	(IEC)	
II.12.1.7	Totalizing wattmeter	TW)	
II.12.1.8	Maximum demand wattmeter	W Pmax 08-02-03	<ol> <li>A type actuated by an integrating meter is shown.</li> <li>Meters which utilize an operating principle other then the mentioned above is expressed as MDW.</li> <li>In the case of maximum demand ammeter (including meters with maximum and minimum indicators),</li> <li>MDA is used.</li> </ol>
II.12.1.9	Varmeter	08-02-04	•
II.12.1.10	Power- factor meter	08-02-05	

II.12.1 Indicating Instrument (Continued)

No.	Name	Graphical symbol	Description
II.12.1.11	Reactive- factor meter	(Sin 9)	
II.12.1.12	Frequency meter	08-02-07	
II.12.1.13	Velocity meter	(IEC)	V is written in a small letter.
II.12.1.14	Tacho- meter	08-02-15	
II.12.1.15	Position indicator	PI	
II.12.1.16	Water level indicator	(IEC)	
II.12.1.17	Ground detector	GD .	
II.12.1.18	Voltage detector	(VD)	Luminous voltage detector is included.

II.12.1 Indicating Instrument (Continued)

No.	Name	Graphical symbol	Description
II.12.1.19	Galvano- meter	08-02-12	
II.12.1.20	Distribu- tion line fault section indicator	SI	
II.12.1.21	Synchro- scope	08-02-08	
II.12.1.22	Thermo- meter	θ 08-02-14	θ may be replaced by t°.
II.12.1.23	Phase meter	9 08-02-06	
II.12.1.24	Maximum- minimum voltmeter or maximum voltmeter	MV .	
II.12.1.25	Maximum ammeter	MA	